

Seat No.: \_\_\_\_\_

Enrollment No. \_\_\_\_\_

## GUJARAT TECHNOLOGICAL UNIVERSITY

BE - SEMESTER- 1<sup>st</sup> / 2<sup>nd</sup> EXAMINATION (NEW SYLLABUS) – SUMMER 2016

Subject Code: 2110006

Date:01/06/2016

Subject Name: Elements of Mechanical Engineering

Time:02:30 PM to 5:00 PM

Total Marks: 70

**Instructions:**

1. Question No. 1 is compulsory. Attempt any four out of remaining Six questions.
2. Make suitable assumptions wherever necessary.
3. Figures to the right indicate full marks.
4. Use of steam table is allowable.

- | Q.1 | Objective Question (MCQ)  | Mark |
|-----|---|------|
| (A) | Select the correct answer   | 07   |
| 1.  | The S.I. unit N-m/s is called<br>(a)Watt (b) Joule (c) Calorie (d) None of the above.   |      |
| 2.  | The Universal gas Constant is equal to<br>(a) M/R (b) R/M (c) M*R (d) All of the above  |      |
| 3.  | The law $PV = C$ is related to this process<br>(a)Adiabatic (b) Isobaric (c) Isochoric (d) Isothermal   |      |
| 4.  | Dryness fraction(x) of superheated steam is<br>(a)equal to 0 (b) greater than 1 (c) less than 1 (d) equal to 1  |      |
| 5.  | Cut-off ratio is related to<br>(a)Carnot cycle (b) Otto cycle (c) Diesel cycle (d) Rankine cycle  |      |
| 6.  | The compression ratio for Diesel engine is in the following range:<br>(a)12 to 22 (b) 5 to 10 (c) 10 to 12 (d) None of the above  |      |
| 7.  | Gear pump and Vane pump are types of<br>(a)Rotary pump (b) Reciprocating pump (c) Centrifugal pump<br>(d) None of the above.  |      |
| (B) | Select the correct answer   | 07   |
| 1.  | The work done on compressor is least when the compression is<br>(a)Isothermal (b) Adiabatic (c) Polytropic (d) None of the above  |      |
| 2.  | Inter cooling in multi stage compression is used to<br>(a) cool air (b) Minimize the work done (c) reduce volume of air<br>(d) none of the above.                       |      |
| 3.  | In the domestic refrigerators the bank of tubes at the back of the refrigerator are<br>(a)Condenser tubes (b) Evaporator tubes (c) Capillary tubes (d) All of the above |      |
| 4.  | Heat is absorbed by refrigerant during refrigeration cycle in<br>(a)Condenser (b) Evaporator (c) Capillary (d) None of the above  |      |
| 5.  | The unit of pressure is<br>(a)Pascal (b) N/m <sup>2</sup> (c) bar (d) all of the above  |      |
| 6.  | The sealing ring for pressure cooker is made from<br>(a)Leather (b) Rubber (c) Plastic (d) Aluminum   |      |
| 7.  | Plate type, Cone type and Centrifugal type are the types of<br>(a)Couplings (b) Brakes (c) Clutches (d) Gear drives   |      |
| Q.2 | (a) Classify the engineering materials.   | 03   |
|     | (b) Explain with neat sketch the working of belt drives and gear drives.  | 04   |
|     | (c) What do you understand by the term 1 ton of refrigeration? What are the main components of vapour compression refrigeration system? Write their functions.          | 07   |

- Q.3** (a) Differentiate between a Brake and a Clutch. **03**  
(b) How the air compressors are classified based on different criteria. **04**  
(c) Draw air standard diesel cycle on p-V and T-s diagrams. Derive its efficiency equation with usual notations. **07**
- Q.4** (a) With neat sketch explain in brief the working of Vane pump. **03**  
(b) Compare: S.I. engines and C.I. engines. **04**  
(c) The following readings were recorded during the test on single cylinder four stroke diesel engine. **07**  
(1) Cylinder diameter = 250 mm  
(2) Stroke length = 350 mm  
(3) Mean effective pressure = 6.7 bar  
(4) Speed of engine = 250 r.p.m.  
(5) Net brake load = 1070 N  
(6) Effective brake drum diameter = 1.5 m  
(7) Fuel consumption rate = 10 kg per hour.  
(8) C.V. of the fuel = 44300 kJ/kg.  
Calculate: (1) Indicated Power (2) Brake Power (3) Mechanical efficiency. (4) Brake thermal efficiency.
- Q.5** (a) Explain the difference between boiler mountings and accessories. **03**  
(b) Calculate the air standard efficiency of the engine working on Otto cycle in which air initially at 1 bar and 20°C is compressed adiabatically to the pressure of 16 bar. Maximum pressure of cycle is 45 bar and adiabatic index  $\gamma = 1.4$ . **04**  
(c) With neat sketch explain the construction and working of **07**  
(i) Fusible plug and (ii) Air pre heater.
- Q.6** (a) Prove that  $C_p - C_v = R$  with usual notations. **03**  
(b) Write a short note on "Solar Energy". **04**  
(c) A cylinder contains 0.6 m<sup>3</sup> of a gas at a pressure of 1 bar and 90 °C. **07**  
The gas is compressed to a volume of 0.18 m<sup>3</sup> by the law  $PV^n = C$ .  
The pressure of gas at the end of compression is 5 bar.  
Calculate: (1) Mass of gas (2) value of index n (3) The change in internal energy of the gas. (4) Work done (5) The heat received or rejected by the gas during the process. Take  $\gamma = 1.4$  and  $R = 0.294$  kJ/kg K.
- Q.7** (a) Explain in brief Open system and closed system giving examples. **03**  
(b) Draw neat and labeled diagram of Cochran Boiler **04**  
(c) Calculate the total amount of heat required to produce 6 kg of steam **07**  
at a pressure of 6 bar and temperature of 258 °C from the water at 30 °C. Take specific heat of steam = 2.1 kJ/kg-K. and the specific heat of water = 4.187 kJ/kg-K.

\*\*\*\*\*