| DIPLOMA ENGINEERING-SEMESTER-VI EXAMINATION-SUMMER 2015 | | | | | | |
|--|--------------------------------|--|--|--|--|--|
| Subject Code: 361907 Subject Name: Refri. And A/C | Date: 06/05/2014 | | | | | |
| U | Total Marks: 70 | | | | | |
| Attempt all questions. Make suitable assumption where ever necessary. Figure to the right indicates full marks. | | | | | | |
| Q-1. (A) Define the terms (any seven) (1) T.R. (2) C.O.P (3) R.H. (4) I.C.L (5) C.F. (6) B.F. (7) SHF (8) Dew point Temperature (9) Relative humidity. | (07) | | | | | |
| Q-1 (B) Any four air-conditioning process explain on psychometric cha | ort. (04) | | | | | |
| Q-1(C) List the human comfort condition for India. | (03) | | | | | |
| Q-2 (A) List the various refrigeration system. Explain Vapor Compress | ion refrigeration system. (04) | | | | | |
| Q-2(B) List the various tubing operation and explain any one. | (03) | | | | | |
| Q-2(C) Derive the Equation of C.O.P for BELL COLEMAN air refriger OR | ration cycle. (07) | | | | | |
| Q-2(C) Explain ammonia water absorption refrigeration system. | (07) | | | | | |
| Q-3 A (1) Explain working of ice plant. | (04) | | | | | |
| (2) List various faults and remedies for split a/c | (03) | | | | | |
| Q-3(B) Explain desirable properties for ideal refrigerant | (07) | | | | | |
| OR | (0.4) | | | | | |
| Q-3 (B) (1) Explain Silent Feature of an ideal insulator material. | (04) | | | | | |
| (2)Explain various air distribution outlet with sketch. | (03) | | | | | |
| Q-4(A) List the various air conditioning and explain any one. | (07) | | | | | |
| Q-4 (B) list the various heat sources (heat load) for air-conditioning des | sign. (04) | | | | | |

Q-4(C) A thick wall 25 cm thick is faced with concrete of 5 cm thick. Thermal conductivity of bricks and concrete is 0.70 W/mkand0.95W/mk if the temperature of bricks and concrete is 30° C

and 5° C .Find the heat loss through wall of $10m \times 5m$.

GUJARAT TECHNOLOGICAL UNIVERSITY

Enroll.no.: _____

(03)

Seat no:_____

Q-5 Solve the Following Example

(1) A F12 vapor refrigeration system working with condensing temperature is 50°C and evaporating temperature is 0°C. The capacity of the system is 7 TR. determine (1). The mass flow rate of R12. (2) The heat rejection. (3) C.O.P. of the system (4) power of compressor. (04)

| 1 | temp°C | Press(bar) | Hf (kj/kg) | Hg (kj/kg) | Sf(kj/kg-k) | Sg(kj/kg-k) |
|---|--------|------------|------------|------------|-------------|-------------|
| 4 | 50 | 12 | 85 | 206 | 0.30 | 0.68 |
| (| 0 | 3 | 36 | 187 | 0.14 | 0.70 |

(2) A Carnot refrigerator required 1.5 kw per tonne of refrigeration to maintain at low temperature of -38°C. Determine 1). C.O.P. 2) Higher temp. 3). C.O.P of heat pump. (03)

OR

(2) Explain sling psychometric

(03)

(3) A bell Coleman cycle operate between 1 bar to 8 bar. Air is compress and cooled up to 29° C and the temperature of cold chamber is 9° C. the compression is follow by $pv^{1.35} = constant$. Calculate C.O.P Of the System and take $c_p=1.003$ kj/kg-k and r=1.4. (07)
